

M E T A F O X



META FOX

NAME OF GAME	META FOX
PC BOARD SIZE	323 (W) × 230 (D) × 30 (H) [mm]
PC BOARD POWER	DC +5V @ 3 A / DC +12 V @ 1 A
PC BOARD CONNECTOR	SEE CONNECTING DIAGRAM



META FOX

DIP SW (2)

ITEM	DESCRIPTION	1	2	3	4	5	6	7	8
DIFFICULTY	C	OFF	OFF						
	A	ON	OFF						
LEVEL	B	OFF	ON						
	D	ON	ON						
1 UP	NOTHING			OFF	OFF				
	60K POINTS			ON	OFF				
	90K POINTS			OFF	ON				
	60/90K POINTS			ON	ON				
NUMBER OF LIVES	3					OFF	OFF		
	5					ON	OFF		
	1					OFF	ON		
	2					ON	ON		
N. C.	OFF POSITION							OFF	
N. C.	COIN 1								OFF
	COIN 2								

PARTS SIDE



DIP SW 1

28



DIP SW 2

VR1

1



META FOX CONNECTING DIAGRAM

SOLDER SIDE			PARTS SIDE
GND	A	1	GND
GND	B	2	GND
+ 5 VDC	C	3	+ 5 VDC
+ 5 VDC	D	4	+ 5 VDC
NC	E	5	NC
+ 12 VDC	F	6	+ 12 VDC
PROTECTION KEY	H	7	PROTECTION KEY
COIN COUNTER 2	J	8	COIN COUNTER 1
COIN LOCKOUT 2	K	9	COIN LOCKOUT 1
SPEAKER (-)	L	10	SPEAKER (+)
NC	M	11	NC
VIDEO GREEN	N	12	VIDEO RED
VIDEO SYNC	P	13	VIDEO BLUE
SERVICE SWITCH	R	14	VIDEO GND
NC	S	15	NC
COIN SWITCH 2	T	16	COIN SWITCH 1
START SWITCH 2	U	17	START SWITCH 1
2P UP	V	18	1P UP
2P DOWN	W	19	1P DOWN
2P LEFT	X	20	1P LEFT
2P RIGHT	Y	21	1P RIGHT
2P A	Z	22	1P A
2P B	a	23	1P B
NC	b	24	NC
NC	c	25	NC
NC	d	26	NC
GND	e	27	GND
GND	f	28	GND